

## 500W Coaxial Attenuator DC-6GHz

### Application

▶ Wireless communication system.

▶ Testing and measuring equipment.

▶ Radar and satellite systems.

▶ Military, Space and Commercial applications.


### RF Characteristics

Part Number	Frequency range	Power	Attenuation Value	Attenuation Tolerance	VSWR Max
5o2050006N10	DC-6GHz	500W	10 dB	±2.0 dB	1.3
5o2050006N20			20 dB	±2.5 dB	1.3
5o2050006N30			30 dB	±1.1 dB	1.3
5o2050006N40			40 dB	±1.1 dB	1.3
5o2050006N50			50 dB	±1.1 dB	1.3
5o2050006N60			60 dB	±1.1 dB	1.3

### Basic Specifications


Impedance	50Ω	Connector Type	N Male to Female
Power	500W	Storage Temperature	-55~+125°C

### Overall Dimension(mm)



Tolerances: ±2% unless otherwise stated.

## Power Derating Diagram



### Notes

- ◆ Coaxial attenuator impedance matched to 50Ω.
- ◆ If necessary, the product shall be air-cooled for auxiliary heat dissipation.
- ◆ For products with a power of over 50W, pay attention to the direction during use and strictly avoid reverse connection.
- ◆ Custom design is available upon request.
- ◆ It supports a one-year standard warranty.